
1.2. Hardware prerequisites

1.2.1. Recommended memory

Before the first installation of the IPDS Kit, print a self test to make sure that your printer has enough memory to support the Kit.

Print the printer self test and check if a minimum of memory is installed.

- HP24x0 (48 MB resident)
- HP3700 Color (64 MB resident)
- HP4000 (16 MB resident) plus a minimum of 8MB RAM memory extension for simplex, and 12 MB for duplex.
- HP4050 (16 MB resident) plus a minimum of 8MB RAM memory extension for simplex, and 12 MB for duplex.
- HP4100N (32 MB resident)
- HP4100mfp (80 MB resident)
- HP4101mfp (80 MB resident)
- HP4200N (64 MB resident)
- HP4250N (128 MB resident)
- HP4300N (64 MB resident)
- HP4350N (128 MB resident)
- HP4345mfp (256 MB resident)
- HP4600 Color (96 MB resident)
- HP4650 Color (160 MB resident)
- HP5000N (12 MB resident) plus a minimum of 8MB RAM memory extension for simplex, and 12 MB for duplex.
- HP5100N (32 MB resident)
- HP5500 Color (96 MB resident)
- HP5550 Color (160 MB resident)
- HP8000N (16 MB resident) plus a minimum of 8MB RAM memory extension for simplex, and 16 MB for duplex.
- HP8100N (16 MB resident) plus a minimum of 8MB RAM memory extension for simplex, and 16 MB for duplex.
- HP8150N (32 MB resident)
- HP9000 (64 MB resident)
- HP9050 (128 MB resident)
- HP9050mfp (256 MB resident)
- HP9000mfp (128 MB resident)
- HP9000Lmfp (128 MB resident)
- HP9055mfp (256 MB resident)
- HP9065mfp (256 MB resident)
- HP9500 Color (160 MB resident)
- HP9500mfp Color (512 MB resident)

1.2.2. Minimum HP firmware date code

- HP24x0 20040625 08.002.0
- HP3700 Color 20030905 06.002.0
- HP4000 970827 MB 3.50
- HP4050 19990309 MB 6.28
- HP4100 20010907 01.019.1
- HP4100mfp 20030322 03.721.0
- HP4200 20020808 04.000.0
- HP4250 20040625 08.002.0
- HP4300 20020905 04.001.0
- HP4350 20040625 08.002.0
- HP4345mfp 20040920 09.004.0
- HP4600 Color 20020801 03.006.0
- HP4650 Color 20040115 07.000.0
- HP5000 MB 3.47
- HP5100
- HP5500 Color 20021217 04.009.0
- HP5550 Color 20040115 07.000.0
- HP8000 980318 MB 4.26

Note : Since the firmware date code 19990305 MB4.48 or higher on the HP8000, the IPDS DIMM version must be the same as HP8100.

- HP8100 MB 5.33
- HP8150 20000830 MB 7.84
- HP9000 20010411 01.000.0
- HP9050 20040603 08.000.0
- HP9050mfp 20040920 08.004.0
- HP9000mfp 20030322 03.721.0
- HP9055mfp 20030322 07.000.0
- HP9065mfp 20030322 07.000.0
- HP9500 Color 20040113 05.004.2
- HP9500mfp 20040920 08.004.0

1.2.3. Network connection

- HP Jet Direct Token ring or an Ethernet card for Hewlett Packard LaserJet printer.

1.3. IBM printers emulated

The Blue kit is fully compatible with the:

- IBM 4028 (Model NS1 and NS2) laser printer and also with,
- IBM 3812 (Models 1 and 2) and
- IBM 3816 (Models O1S, O1D).
- IBM 43XX.